




## Technical specifications

Type		3RF22 ..-1....	3RF22 ..-2....	3RF22 ..-3....
<b>General data</b>				
<b>Ambient temperature</b>				
• During operation, derating from 40 °C	°C	-25 ... + 60		
• During storage	°C	-55 ... + 80		
<b>Installation altitude</b>				
	m	0 ... 1000; > 1000 ask Technical Assistance		
<b>Shock resistance</b>				
acc. to IEC 60068-2-27	g/ms	15/11		
<b>Vibration resistance</b>				
acc. to IEC 60068-2-6	g	2		
<b>Degree of protection</b>				
		IP20		
<b>Insulation strength</b> at 50/60 Hz (main/control circuit to floor)				
	V rms	4000		
<b>Electromagnetic compatibility (EMC)</b>				
• Emitted interference				
- Conducted interference voltage acc. to IEC 60947-4-3		Class A for industrial applications <sup>1)</sup>		
- Emitted, high-frequency interference voltage acc. to IEC 60947-4-3		Class A for industrial applications		
• Interference immunity				
- Electrostatic discharge acc. to IEC 61000-4-2 (corresponds to degree of severity 3)	kV	Contact discharge 4; air discharge 8; behavior criterion 2		
- Induced RF fields acc. to IEC 61000-4-6	MHz	0.15 ... 80; 140 dBµV; behavior criterion 1		
- Burst acc. to IEC 61000-4-4	kV	2/5.0 kHz; behavior criterion 1		
- Surge acc. to IEC 61000-4-5	kV	Conductor - ground 2; conductor - conductor 1; behavior criterion 2		
<b>Connection type</b>				
		 <b>Screw terminals</b>	 <b>Spring-type terminals</b>	 <b>Ring terminal lug connection</b>
<b>Connection, main contacts</b>				
• Conductor cross-section				
- Solid	mm <sup>2</sup>	2 x (1.5 ... 2.5) <sup>2)</sup> , 2 x (2.5 ... 6) <sup>2)</sup>	2 x (0.5 ... 2.5)	--
- Finely stranded with end sleeve	mm <sup>2</sup>	2 x (1 ... 2.5) <sup>2)</sup> , 2 x (2.5 ... 6) <sup>2)</sup> , 1 x 10	2 x (0.5 ... 1.5)	--
- Finely stranded without end sleeve				
- Solid or stranded, AWG cables	mm <sup>2</sup>	-- 2 x (AWG 14 ... 10)	2 x (0.5 ... 2.5) 2 x (AWG 18 ... 14)	--
• Stripped length	mm	10	10	
• Terminal screw				
- Tightening torque,	Nm	M4 2 ... 2.5	--	M5 2.5 ... 2
∅ 5 ... 6 mm, PZ 2	lb.in	18 ... 22		18 ... 22
• Cable lug				
- Acc. to DIN 46234		--	--	5-2.5 ... 5-25
- Acc. to JIS C 2805				R 2-5 ... 14-5
<b>Connection, auxiliary/control contacts</b>				
• Conductor cross-section, with or without end sleeve				
	mm	1 x (0.5 ... 2.5), 2 x (0.5 ... 1.0)	0.5 ... 2.5	1 x (0.5 ... 2.5), 2 x (0.5 ... 1.0)
	AWG	20 ... 12	20 ... 12	20 ... 12
• Stripped length				
	mm	7	10	7
• Terminal screw				
- Tightening torque,	Nm	M3 0.5 ... 0.6	--	M3 0.5 ... 0.6
∅ 3.5, PZ 1	lb.in	4.5 ... 5.3		4.5 ... 5.3

<sup>1)</sup> These products were built as Class A devices. The use of these devices in residential areas could result in lead in radio interference. In this case these may be required to introduce additional interference suppression measures.

<sup>2)</sup> If two different conductor cross-sections are connected to one clamping point, both cross-sections must lie in the range specified. If identical cross-sections are used, this restriction does not apply.

# Solid-State Switching Devices for Resistive Loads

## Solid-State Relays

### 3RF22 solid-state relays, three-phase, 45 mm

Order No.	$I_{\max}^{1)}$ at $R_{\text{thha}}/T_u = 40\text{ °C}$		$I_e$ acc. to IEC 60947-4-3 at $R_{\text{thha}}/T_u = 40\text{ °C}$		$I_e$ acc. to UL/CSA at $R_{\text{thha}}/T_u = 50\text{ °C}$		Power loss at $I_{\max}$ W	Minimum load current A	Max. leakage current mA
	A	K/W	A	K/W	A	K/W			
<b>Main circuit</b>									
3RF22 30-. AB..	30	0.57	30	0.57	30	0.44	81	0.5	10
3RF22 55-1AB..	55	0.18	50	0.27	50	0.19	151	0.5	10
3RF22 55-2AB..			20	1.83	20	1.58			
3RF22 55-3AB..			50	0.27	50	0.19			
3RF22 30-. AC..	30	0.33	30	0.33	30	0.25	122	0.5	10
3RF22 55-1AC..	55	0.09	50	0.15	50	0.1	226	0.5	10
3RF22 55-2AC..			20	1.19	20	1.02			
3RF22 55-3AC..			50	0.15	50	0.1			

1)  $I_{\max}$  provides information about the performance of the solid-state relay. The actual permitted rated operational current  $I_e$  can be smaller depending on the connection method and cooling conditions.

*Note: The required heat sinks for the corresponding load currents can be determined from the characteristic curves. The minimum thickness values for the mounting surface must be observed.*

Order No.	Rated impulse withstand capacity $I_{\text{tsm}}$		$I^2t$ value A <sup>2</sup> s
	A		
<b>Main circuit</b>			
3RF22 30-....5	300		450
3RF22 55-....5	600		1800

Type		3RF22 ...-AB.5	3RF22 ...-AC.5
<b>Main circuit</b>			
<b>Controlled phases</b>		Two-phase	Three-phase
<b>Rated operational voltage <math>U_e</math></b>	V	48 ... 600	48 ... 600
• Operating range	V	40 ... 660	40 ... 660
• Rated frequency	Hz	50/60 ± 10 %	50/60 ± 10 %
<b>Rated insulation voltage <math>U_i</math></b>	V	600	600
<b>Rated impulse withstand voltage <math>U_{\text{imp}}</math></b>	kV	6	6
<b>Blocking voltage</b>	V	1200	1200
<b>Rage of voltage rise</b>	V/μs	1000	1000

Type		3RF22 ...-A.3.	3RF22 ...-A.4.
<b>Control circuit</b>			
<b>Method of operation</b>		AC operation	DC operation
<b>Rated control supply voltage <math>U_s</math></b>	V	110	4 ... 30
<b>Rated frequency</b> of the control supply voltage		50/60 ± 10 %	--
<b>Control supply voltage, max.</b>	V	121	30
<b>Typical actuating current</b>	mA	15	30
<b>Response voltage</b>	V	90	4
<b>Drop-out voltage</b>	V	< 40	1
<b>Operating times</b>			
• ON-delay	ms	40 + max. one half-wave	1 + max. one half-wave
• OFF-delay	ms	40 + max. one half-wave	1 + max. one half-wave

# Solid-State Switching Devices for Resistive Loads

## Solid-State Relays

### 3RF22 solid-state relays, three-phase, 45 mm

#### Fused version with semiconductor protection (similar to type of coordination "2")<sup>1)</sup>

The semiconductor protection for the 3RF22 controls can be used with different protective devices. Siemens recommends the use of special SITOR semiconductor fuses. The table below lists the maximum permissible fuses for each 3RF22 control.

If a fuse is used with a higher rated current than specified, semiconductor protection is no longer guaranteed. However, smaller fuses with a lower rated current for the load can be used without problems.

Order No.	All-range fuses		Semiconductor fuses/partial-range fuses			
	LV HRC design gR/SITOR	Cylindrical design gR/NEOZED <sup>2)</sup> SILIZED 5SE1	LV HRC design aR/SITOR	Cylindrical design aR/SITOR	aR/SITOR 14 mm x 51 mm 3NC1 4	aR/SITOR 22 mm x 58 mm 3NC2 2
	3NE1		3NE8	3NC1 0		
<b>Operational voltage <math>U_e</math> up to 460 V (+10 %)</b>						
3RF22 30-.....	3NE1 814-0 <sup>3)</sup>	5SE1 325 <sup>3)</sup>	3NE8 003-1	3NC1 032	3NC1 430	3NC2 232
3RF22 55-.....	3NE1 802-0 <sup>3)</sup>	5SE1 350 <sup>3)</sup>	3NE8 018-1	--	3NC1 450	3NC2 263
<b>Operational voltage <math>U_e</math> up to 600 V (+10 %)</b>						
3RF22 30-.....	3NE1 814-0 <sup>3)</sup>	--	3NE8 003-1	3NC1 025 <sup>3)</sup>	3NC1 430	3NC2 232
3RF22 55-.....	3NE1 803-0 <sup>3)</sup>	--	3NE8 018-1	--	3NC1 450 <sup>3)</sup>	3NC2 250 <sup>3)</sup>

Order No.	Cable and line protection fuses				
	LV HRC design <sup>3)</sup> gG	Cylindrical design <sup>3)</sup> gG	gG	gG	DIAZED <sup>3)</sup> quick
	3NA3	10 mm x 38 mm 3NW6 0	14 mm x 51 mm 3NW6 1	22 mm x 58 mm 3NW6 2	5SB
<b>Operational voltage <math>U_e</math> up to 460 V (+10 %)</b>					
3RF22 30-.....	3NA3 803-6	--	3NW6 101-1	3NW6 205-1	5SB 1 71
3RF22 55-.....	3NA3 807-6	--	--	--	5SB 3 11
<b>Operational voltage <math>U_e</math> up to 600 V (+10 %)</b>					
3RF22 30-.....	3NA3 803-6	--	--	--	--
3RF22 55-.....	3NA3 805-6	--	--	--	--

Suitable fuse holders, fuse bases and controls can be found in "BETA Low-Voltage Circuit Protection".

<sup>1)</sup> Type of coordination "2" according to EN 60947-4-1:  
In the event of a short-circuit, the controls in the load feeder must not endanger persons or the installation. They must be suitable for further operation. For fused configurations, the protective device must be replaced.

<sup>2)</sup> For use only with operational voltage  $U_e$  up to 400 V.

<sup>3)</sup> These fuses have a smaller rated current than the solid-state relays.