

# SIRIUS 3RW Soft Starters

## 3RW44 Soft Starters for High-Feature Applications

3RW44

### More information

#### Application examples for normal starting (Class 10)

**Normal starting Class 10** (up to 20 s with 350 %  $I_{n \text{ motor}}$ ).

The soft starter rating can be selected to be as high as the rating of the motor used

Application	Conveyor belt	Roller conveyor	Compressor	Small fans <sup>1)</sup>	Pump	Hydraulic pump
<b>Starting parameters</b>						
• Voltage ramp and current limiting						
- Starting voltage	%	70	60	50	30	30
- Starting time	s	10	10	10	10	10
- Current limit value		Deactivated	Deactivated	$4 \times I_M$	$4 \times I_M$	Deactivated
• Torque ramp						
- Starting torque		60	50	40	20	10
- End torque		150	150	150	150	150
- Starting time		10	10	10	10	10
• Breakaway pulse						
		Deactivated (0 ms)	Deactivated (0 ms)	Deactivated (0 ms)	Deactivated (0 ms)	Deactivated (0 ms)
<b>Ramp-down mode</b>						
		Smooth ramp-down	Smooth ramp-down	Free ramp-down	Free ramp-down	Pump ramp-down
				Free ramp-down		Free ramp-down

#### Application examples for heavy starting (Class 20)

**Heavy starting Class 20** (up to 40 s with 350 %  $I_{n \text{ motor}}$ ).

The soft starter has to be selected one performance class higher than the motor used

Application	Stirrer	Centrifuge	Milling machine
<b>Starting parameters</b>			
• Voltage ramp and current limiting			
- Starting voltage	%	30	30
- Starting time	s	30	30
- Current limit value		$4 \times I_M$	$4 \times I_M$
• Torque ramp			
- Starting torque		30	30
- End torque		150	150
- Starting time		30	30
• Breakaway pulse			
		Deactivated (0 ms)	Deactivated (0 ms)
<b>Ramp-down mode</b>			
		Free ramp-down	Free ramp-down or DC braking
		Free ramp-down	

#### Application examples for very heavy starting (Class 30)

**Very heavy starting Class 30** (up to 60 s with 350 %  $I_{n \text{ motor}}$ ).

The soft starter has to be selected two performance classes higher than the motor used

Application	Large fans <sup>2)</sup>	Mill	Breakers	Circular saw/bandsaw
<b>Starting parameters</b>				
• Voltage ramp and current limiting				
- Starting voltage	%	30	50	30
- Starting time	s	60	60	60
- Current limit value		$4 \times I_M$	$4 \times I_M$	$4 \times I_M$
• Torque ramp				
- Starting torque		20	50	20
- End torque		150	150	150
- Starting time		60	60	60
• Breakaway pulse				
		Deactivated (0 ms)	80 %; 300 ms	Deactivated (0 ms)
<b>Ramp-down mode</b>				
		Free ramp-down	Free ramp-down	Free ramp-down
		Free ramp-down	Free ramp-down	Free ramp-down

1) The mass inertia of the fan is < 10 times the mass inertia of the motor

2) The mass inertia of the fan is  $\geq 10$  times the mass inertia of the motor

#### Note:

These tables present sample set values and device sizes. They are intended only for the purposes of information and are not binding. The set values depend on the application in question and must be optimized during commissioning.

The soft starter dimensions should be checked where necessary with the Win-Soft Starter software or with the help of Technical Assistance.