

Switching of lamps

			Remote control switches				
			5TT4 101 5TT4 102 5TT4 105 5TT4 115	5TT4 103 5TT4 104	5TT4 12 5TT4 15	5TT4 13 5TT4 14	
Switching of transformers for halogen lamps			W	1200			
Fluorescent and compact lamps in ballast operation							
• Uncorrected	L18W	Unit(s)	35	30			
	L36W	Unit(s)	35	30			
	L58W	Unit(s)	25	20			
• Parallel-corrected	L18W/4.5 μ F	Unit(s)	40	50			
	L36W/4.5 μ F	Unit(s)	40	50			
	L58W/7 μ F	Unit(s)	28	30			
• DUO switching, 2-lamp	L18W	Unit(s)	2 x 30	2 x 24			
	L36W	Unit(s)	2 x 30	2 x 24			
	L58W	Unit(s)	2 x 30	2 x 16			
Fluorescent and compact lamps with electronic ballast (ECG)							
• AC operation, 1-lamp	L18W	Unit(s)	36	30			
	L36W	Unit(s)	36	30			
	L58W	Unit(s)	24	20			
• AC operation, 2-lamp	L18W/4.5 μ F	Unit(s)	2 x 22	2 x 18			
	L36W/4.5 μ F	Unit(s)	2 x 22	2 x 18			
	L58W/7 μ F	Unit(s)	2 x 15	2 x 12			

The specified values are intended to serve as a guideline, the max. number of illuminants may vary, depending on the manufacturer. The values specified here refer to Osram illuminants and ballasts.