

More information

		PM-D power modules 3RK1 903-0BA00
Rated control supply voltage U_s up to 60 °C	V	20.4 ... 28
Rated operational current I_e		
• Recommended short-circuit protection	A	10
• Melting fuse	A	10
• Miniature circuit breakers	A	10, tripping characteristic B
Power consumption from the backplane bus	mA	≤ 10
Supplying		
• Motor starters		Yes
• Frequency converters		Yes
• Motor starters for safety technology		No
• Solid-state modules		No
• Ex(i) modules		No
Alarms		None
Diagnostics functions		Yes
• System fault/device fault		Red "SF" LED
• Monitoring the supply voltage for solid-state modules U_1		Green "PWR" LED
• Monitoring the supply voltage for contactors U_2		Green "CON" LED
• Diagnostics information can be read out		Yes
Conductor cross-sections		
• Flexible with end sleeve	mm ²	1.5
• Rigid	mm ²	2.5
Mounting dimensions (W x H x D)	mm	15 x 195.5 x 117.5